

Go Music Erhu

Go Music Multi-frequency Erhu Transmitter

The OSL Go Music Erhu perfectly fits over the instrument using the position clips and delivers crystal clear audio reproduction. It can be connected directly to the Go Music receiver for maximum musician flexibility or to the Q500 receivers for a professional set-up. The IR connect offers instant synchronisation between the receiver & the transmitter. The receiver also has a 30dB gain control for self monitoring. Built for musicians, the setup is quick and easy with the antenna's prefixed onto the system. The whole system is designed to be small enough to fit into your instrument case or travel bags with ease



Technical Specifications

Type	Condenser
Frequency Range	30 Hz - 22 kHz
RF Range	60m, Line of Sight
Frequency Bands	C: 734 - 776 MHz; GB: 606 - 648 MHz; E: 823 - 865 MHz; D: 780 - 822 MHz
RF Output	Max. 30 mW
Operation Time	8 Hours
Power Supply	2 AA batteries, 1.5 V

Dimensions

Height	84 mm
Width	35 mm
Depth	29 mm
Net Weight	70 gms