

OD1000-CS6PoE

6" Rimless PoE Ceiling Speaker with Dante & DSP Processing

The OSL OD1000 Dante Systems offer quick & reliable solutions to systems integrators. The OD1000-CS6PoE Rimless ceiling mount system can be powered using the POE power supply or 24 VDC. Audio transmission and signal control is achieved via a RJ45 Ethernet port. This allows seamless connection to the Dante Network. The CS6PoE also has an inbuilt DSP and can power and additional speaker with its 30W output.



Technical Specifications

Audio Interface	RJ 45
Audio Signal Input & Control	Dante
Output Power	30W x 2
Transmission Rate	100M / 1000M bps
Frequency Range	80Hz - 20kHz
Sensitivity	93dB (1w/m)
Max SPL	108 dB

Dimensions

Depth	40 mm
Diameter	164 mm
Net Weight	1.3 Kgs