

## Q500.2R

Dual channel true diversity receiver

The OSL Q500 series offers users upto 16 simultaneous operating channels, over a PLL synthesized circuit and anti-interference support. The Q500.2R True-Diversity dual channel receiver comes in a 19" rack size and can be mounted using the rack mount accessory. The RF range for the receiver is 100m (Line of Sight)



### Technical Specifications

Diversity Principle	True Diversity
Operating Channels	16 Channels Simultaneous Use
Frequency Selection	Auto Selection with IR Sync
Frequency Bands	C: 734 - 776 MHz; GB: 606 - 648 MHz; E: 823 - 865 MHz; D: 780 - 822 MHz
Frequency Range	20 Hz - 20 kHz
Modulation	Wideband FM
Power Supply	DC12V-18V / 500mA

### Dimensions

Height	44 mm
Width	483 mm
Depth	333 mm
Net Weight	4.8 kgs